



| Modelo<br>Model                                       | LPL0620NBAS        | LPL1240NBAS  | LPL1550NBAS  |
|---|--------------------|--------------|--------------|
| Tensión entrada nominal<br>Input voltage              | 230V               | 230V         | 230V         |
| Frecuencia entrada nominal<br>Input frequency         | 50Hz               | 50Hz         | 50Hz         |
| Rango de frecuencia de entrada<br>Input voltage range | 50Hz-60Hz          | 50Hz-60Hz    | 50Hz-60Hz    |
| Potencia<br>Power                                     | 20W                | 40W          | 50W          |
| Número de LEDs<br>Number of LEDs                      | 120 LEDs SMD       | 240 LEDs SMD | 312 LEDs SMD |
| Flujo lumínico<br>Lumen                               | 2715Lm             | 5430Lm       | 6787Lm       |
| Temperatura de color<br>Color temperature             | 5000K□             | 5000K□       | 5000K□       |
| Ángulo<br>Angle                                       | 120°               | 120°         | 120°         |
| Largo<br>Length                                       | 600mm              | 1200mm       | 1500mm       |
| Ancho x alto<br>Width x height                        | 80x65mm            | 80x65mm      | 80x65mm      |
| Base y difusor<br>Base and diffuser                   | Policarbonato / PC |              |              |
| IP  | 65                 | 65           | 65           |
| Sensor<br>Sensor                                      | Sí (Microondas)    |              |              |
| IK  | IK10               | IK10         | IK10         |



LPL0620NBAS  
LPL1240NBAS  
LPL1550NBAS



Sensor por microondas  
fácilmente ajustable

## PANTALLA NBAS

### COMO POR ARTE DE MAGIA

El sensor microondas instalado en el interior de esta gama, alcanza tal grado de precisión que parece magia. Se anticipa al movimiento del usuario manteniendo iluminadas las zonas requeridas sin necesidad de pulsadores, temporizadores o realizar movimientos extraños para que nos detecte el sensor. La solución más práctica y eficiente.

### AS BY ART OF MAGIC

The microwave sensor installed inside this range achieves such a degree of precision that it seems like magic. It anticipates the user's movement by keeping the required areas illuminated without the need for push buttons, timers or strange movements for the sensor to detect us. The most practical and efficient solution.

